## 730 / 590 Firmware update procedure

2019.04.26

## 1 Run the OPTIMUM 2 TOSHIBA\_M343 app



Firmware			
Mount EO V	Device TMPM343FDXBG (TOSHIBA)	Item code SGV 730 FW2Box ver. 10003530	
Firmware update	SM adjustment Focus Adjustment OS	centering Reading FW version Serial No. Scal	e adjustment
<ul><li>2 Sel</li><li>3 Sel</li><li>4 Clic</li></ul>	ect "Firmware upd ect mount type ck "Connect" butto	ate" tab n	
FW2B	ox should be the la	atest version.	
Last comman	d:		
L			

			Item code		
Load S	IG file (Sub/OS CPU)	HIBA )	SGV 730		
Write S	SIG file		FW2Box ver.		
Write S	SIG file <mark>(</mark> Sub/OS CPU)		10003530		
FW2Bo	ox firmware update	nent OS centerio		Serial No.	Scale adjustme
Exit		lienc   05 centering	g Reading two version	Senarivo.	Jocale aujustitie
(5 (6	Click "Firmwa) Click "Load S	dual adjustment data are" SIG file"			
(5 (6	Remove individ ) Click "Firmwa ) Click "Load S	dual adjustment data are" SIG file"			



8	Optimum II for New TOSHIBA M343 CPU	Ver. 1.6.2	
9	Load SIG file Load SIG file (Sub/OS CPU) Write SIG file Write SIG file (Sub/OS CPU)	HIBA )	FW2Box ver. 10003530
	FW2Box firmware update Exit	nent OS centering	Reading FW version Serial No. Scale adjustment
	<ul> <li>Remove individual adju</li> <li>8 Click "Firmware"</li> <li>9 Click "Write SIG f</li> <li>10 Wait until 100%</li> </ul>	istment data	Progress 19 %
	Last command : Load SIG file Copyright	(C) 2005	II Firmware update succeeded ! Please click [Connect] button again to continue further operation.
ļ			ОК

nware				
ount	Device	Item code		
F0 •	TMPM343EDVBG (TOSHIBA)	SGV 730		
		FW2Box ver.		
Connect	(1) Click "Connect"	10003530		
mware update H	SM adjustment   Focus Adjustment   OS centering   Re	ading FW version	Serial No.	Scale adjustment
File name	2: 730 ed6xxxx 101075d0xx36.sig			6
Last command	d:			

## Scale adjustment is required after updating the firmware version



Please set the lens horizontally as shown above.

Optimum II for New TOSHIBA M343 CPU Ver. 1.6.2	
Firmware Mount EO Connect Device TMPM343FDXBG (TOSHIBA) Firmware update HSM adjustment Focus Adjustment OS centering Read Attach lens on adjustment base 12 Select "Scale adjustment" tab 13 Click "OK"	Item code SGV 730 FW2Box ver. 10003530 ding FW version Serial Nc, Scale adjustment - SC/1 -
	ОК
Copyright (C) 2005 - 2017 SIGMA Co	prporation

Doptimum II for New TOSHIBA M343 CPU Ver. 1.6.2					
Firmware					
Mount Device Item code					
	SGV 730				
	FW2Box ver.				
Connect	10003530				
Firmware undate HSM adjustment Focus Adjustment OS centering P	eading EW version Serial No. Scale adjustment				
Scale adjustment done successfully	- OS/2 -				
(4) Please confirm the message					
(15) Click "Finish"					
	(15) Finish				
Copyright (C) 2005 - 2017 SIGMA Corporation					